

EPROM/FLASH Simulator

- 8, 16 or 32 Bit Operation
- 2, 8, 16 or 64 MBit Versions
- DIL or PLCC Adapters
- SO Adapter
- TSOP Adapter
- ESI-CON for In-Circuit Simulation
- Monitor Control
- NMI and RESET Generation

The EPROM simulator replaces up to 2 EPROMs on the target system. They can work in 8 or 16 bit mode. A 40 pin target adapter replaces 16 bit EPROMs. Banked EPROMs may be simulated too. Two EPROM simulators are used to build a 32-bit emulation system.

The EPROM simulator support communication functions. Therefore monitor programs can communicate very fast with the host system. The download speed is up to 100 KByte/sec. (400 KByte/sec. on ESI/64M). All TRACE32 monitor systems support this interface.

Features

Function

The EPROM simulator replaces up to 2 EPROMs on the target system. They can work in 8 or 16 bit mode. A 40 pin target adapter replaces 16 bit EPROMs. Banked EPROMs may be simulated too. Two EPROM simulators are used to build a 32-bit emulation system.

- 8 and 16 Bit Emulation
- Simulates two 8 Bit or one 16 Bit EPROM
- Support of banked EPROMs
- 2 or 8 Mbit totally
- 70/40ns Access Time
- High-Speed Download
- Reset Function for Target
- ROM Monitor Interface
- Operation together with BDM Debugger
- Expansion Capability
 - 32 Bit Operation with 2 Simulators
 - 64 Bit Operation with 4 Simulators

Supported EPROM Pinouts

8 Bit DIL adapter				
A19	1	32	VCC	
A16	2	31	A18	
A15	3	30	A17	
A12	4	29	A14	
A07	5	28	A13	
A06	6	27	A08	
A05	7	26	A09	
A04	8	25	A11	
A03	9	24	/OE	
A02	10	23	A10	
A01	11	22	/CE	
A00	12	21	D07	
D00	13	20	D06	
D01	14	19	D05	
D02	15	18	D04	
GND	16	17	D03	

Note: For 28 (24) pin EPROMS VCC is required on pin 30 (28).


16 Bit DIL adapter

A18	1	40	VCC
/CE	2	39	A17
D15	3	38	A16
D14	4	37	A15
D13	5	36	A14
D12	6	35	A13
D11	7	34	A12
D10	8	33	A11
D09	9	32	A10
D08	10	31	A09
GND	11	30	GND
D07	12	29	A08
D06	13	28	A07
D05	14	27	A06
D04	15	26	A05
D03	16	25	A04
D02	17	24	A03
D01	18	23	A02
D00	19	22	A01
/OE	20	21	A00


16 Bit DIL adapter
(8/16 MBit)

A18	1	42	A19
A17	2	41	A08
A07	3	40	A09
A06	4	39	A10
A05	5	38	A11
A04	6	37	A12
A03	7	36	A13
A02	8	35	A14
A01	9	34	A15
A00	10	33	A16
/CE	11	32	A20
GND	12	31	A21
/OE	13	30	D15
D00	14	29	D07
D08	15	28	D14
D01	16	27	D06
D09	17	26	D13
D02	18	25	D05
D10	19	24	D12
D03	20	23	D04
D11	21	22	VCC


8 bit PLCC adapter
EPROM mode




8 bit PLCC adapter
FLASH mode



16 bit PLCC adapter



SO44



TSOP32	A11	1	32	/OE
	A09	2	31	A10
	A08	3	30	/CE
	A13	4	29	D07
	A14	5	28	D06
	A17	6	27	D05
	N/C	7	26	D04
	VCC	8	25	D03
	A18	9	24	GND
	A16	10	23	D02
	A15	11	22	D01
	A12	12	21	D00
	A07	13	20	A00
	A06	14	19	A01
	A05	15	18	A02
	A04	16	17	A03
TSOP40	A16	1	40	A17
	A15	2	39	GND
	A14	3	38	A20
	A13	4	37	A19
	A12	5	36	A10
	A11	6	35	D07
	A09	7	34	D06
	A08	8	33	D05
	N/C	9	32	D04
	N/C	10	31	VCC
	N/C	11	30	VCC
	PULLUP	12	29	A21
	A18	13	28	D03
	A07	14	27	D02
	A06	15	26	D01
	A05	16	25	D00
	A04	17	24	/OE
	A03	18	23	GND
	A02	19	22	/CE
	A01	20	21	A00

TSOP48 8 bit	A16	1	48	A17
	A15	2	47	N/C
	A14	3	46	GND
	A13	4	45	A00
	A12	5	44	D07
	A11	6	43	N/C
	A10	7	42	D06
	A09	8	41	N/C
	A20	9	40	D05
	A21	10	39	N/C
	N/C	11	38	D04
	N/C	12	37	VCC
	A22	13	36	N/C
	N/C	14	35	D03
	PULLUP	15	34	N/C
	A19	16	33	D02
	A18	17	32	N/C
	A08	18	31	D01
	A07	19	30	N/C
	A06	20	29	D00
	A05	21	28	/OE
	A04	22	27	GND
	A03	23	26	/CE
	A02	24	25	A01

TSOP48 16 bit	A15	1	48	A16
	A14	2	47	N/C
	A13	3	46	GND
	A12	4	45	D15
	A11	5	44	D07
	A10	6	43	D14
	A09	7	42	D06
	A08	8	41	D13
	A19	9	40	D05
	A20	10	39	D12
	N/C	11	38	D04
	N/C	12	37	VCC
	A21	13	36	D11
	N/C	14	35	D03
	PULLUP	15	34	D10
	A18	16	33	D02
	A17	17	32	D09
	A07	18	31	D01
	A06	19	30	D08
	A05	20	29	D00
	A04	21	28	/OE
	A03	22	27	GND
	A02	23	26	/CE
	A01	24	25	A00

Signal	Pin	Pin	Signal
GND	1	2	GND
A11	3	4	A12
A10	5	6	A13
A09	7	8	A14
A08	9	10	A15
A07	11	12	A16
A06	13	14	A17
A05	15	16	A18
A04	17	18	A19
A03	19	20	A20
A02	21	22	A21
A01	23	24	A22
A00	25	26	A23
(OPFETCH-)*	27	28	(WRITE-)*
CE_LOWERBYTE-	29	30	OE_LOWERBYTE-
D00	31	32	D01
D02	33	34	D03
D04	35	36	D05
D06	37	38	D07
GND	39	40	VCC_TARGET
GNDS	41	42	RESET+/-
VCCS	43	44	NMI+/-
WORD_SELECT-	45	46	(CYCLE-)*
GND	47	48	GND
CE_UPPERBYTE-	49	50	OE_UPPERBYTE-
D08	51	52	D09
D10	53	54	D11
D12	55	56	D13
D14	57	58	D15
GND	59	60	GND
VCC_BUFFER	61	62	VCC_3VOLT
VCC_INTERN	63	64	VCC_TARGET

ESICON adapter

(*) Signals only necessary for RISC Trace

Order Information

Module Description

OrderNo Code	Text
LA-7492 ESI/16M/40	EPROM Simulator 16 MBit supports devices up to 16 MBit, 8 and 16 Bit, 40ns access time, including adapter for DIL28/32 and DIL40 supports up to two ROM Monitor licenses
LA-7494 ESI/64M/40	EPROM Simulator 64 MBit supports devices up to 64 MBit, 8 and 16 Bit, 40ns access time, including adapter for DIL28/32 and DIL40, supports up to two ROM Monitor licenses
LA-7493 ESI/16M/40- 3.3V	EPROM Simulator 16 MBit 3.3V supports devices up to 16 MBit, 8 and 16 Bit, 40ns access time, 3.3V including adapter for DIL28/32 and DIL40, supports up to two ROM Monitor licenses
LA-7480 ESI-DIL42	Adapter for DIL42 adapter for 16-bit DIL-EPROM, connection to DIL42 for 16, 32 and 64 MBit EPROM
LA-7505 ESI-PLCC32	Adapters for PLCC32 2 adapters for 8-Bit PLCC-EPROMs (10,6 mm), connection to PLCC32
LA-7483 ESI-PLCC32- SHORT	Adapters for PLCC32-SHORT 2 short adapters for 8-Bit PLCC-EPROMs (4,5 mm), connection to PLCC32
LA-7506 ESI-PLCC44	Adapter for PLCC44 adapter for 16-Bit PLCC-EPROM (10,6 mm), connection to PLCC44
LA-7509 ESI-CON-SO44	Converter for SO44 Converter from DIL40 to SO44 package (1.27mm x 16mm) for 16-Bit Flash

OrderNo Code	Text
LA-7481 ESI-SO44	Adapter for SO44 adapter for 16-bit EPROM, connection to SO44 for 16 MBit EPROM
LA-7482 ESI-CON	Universal EPROM Simulator Adapter 8/16 Bit Adapter to ESI-CON universal connector, supports 8 and 16 bit, 3,3 V and 5 V devices, up to 64 MBit, high-speed download 500 KByte/sec.
LA-7471 ESI-TSSOP48-16	Adapter for TSSOP48 16 Bit Adapter for 16-Bit TSSOP FLASH devices, connection from ESICON to TSSOP48, use with ESI-CON adapter
LA-7472 ESI-TSSOP48-8	Adapter for TSSOP48 8 Bit Adapter for 8-Bit TSSOP FLASH devices, connection from ESICON to TSSOP48, use with ESI-CON adapter
LA-7473 ESI-TSSOP40	Adapter for TSSOP40 8 Bit Adapter for 8-Bit TSSOP FLASH devices, connection from ESICON to TSSOP40, use with ESI-CON adapter

Detailed Order Information

Order No.	Code	Text
LA-7492	ESI/16M/40	EPROM Simulator 16 MBit
LA-7494	ESI/64M/40	EPROM Simulator 64 MBit
LA-7493	ESI/16M/40-3.3V	EPROM Simulator 16 MBit 3.3V
LA-7480	ESI-DIL42	Adapter for DIL42
LA-7505	ESI-PLCC32	Adapters for PLCC32
LA-7483	ESI-PLCC32-SHORT	Adapters for PLCC32-SHORT
LA-7506	ESI-PLCC44	Adapter for PLCC44
LA-7509	ESI-CON-SO44	Converter for SO44
LA-7481	ESI-SO44	Adapter for SO44
LA-7482	ESI-CON	Universal EPROM Simulator Adapter 8/16 Bit
LA-7471	ESI-TSSOP48-16	Adapter for TSSOP48 16 Bit
LA-7472	ESI-TSSOP48-8	Adapter for TSSOP48 8 Bit
LA-7473	ESI-TSSOP40	Adapter for TSSOP40 8 Bit

Contact

International Representative

Argentina

Anacom Eletronica Ltda.
Mr. Rafael Sorice
Rua Nazareth, 807, Barcelona
BR-09551-200 São Caetano do Sul, SP
Phone: +55 11 3422 4200
FAX: +55 11 3422 4242
EMAIL: rsorice@anacom.com.br

Australia

Embedded Logic Solutions P/L
Mr. Ramzi Kaffan
Suite 2, Level 3
144 Marsden Street
Parramatta NSW 2150
Phone: +61 2 9687 1880
FAX: +61 2 9687 1881
EMAIL: sales@emlogic.com.au

Austria

Lauterbach GmbH
Alltaufstr. 40
D-85635 Höhenkirchen-Siegertsbrunn
Phone: +49 8102 9876 190
FAX: +49 8102 9876 187
EMAIL: sales@lauterbach.com

Belgium

Tritec Benelux B.V.
Mr. Robbert de Voogt
Stationspark 550
NL-3364 DA Sliedrecht
Phone: +31 184 41 41 31
FAX: +31 184 42 36 11
EMAIL: software@tritec.nl

Brazil

Anacom Eletronica Ltda.
Mr. Rafael Sorice
Rua Nazareth, 807, Barcelona
BR-09551-200 São Caetano do Sul, SP
Phone: +55 11 3422 4200
FAX: +55 11 3422 4242
EMAIL: rsorice@anacom.com.br

Canada

Lauterbach Inc.
Mr. Udo Zoettler
4 Mount Royal Ave.
USA-Marlborough, MA 01752
Phone: +1 508 303 6812
FAX: +1 508 303 6813
EMAIL: info_us@lauterbach.com

China Beijing

Lauterbach Technologies Co., Ltd
Mr. Linglin He
Beijing Office
A3, South Lishi Road, XiCheng District
Beijing 100037, P.R. China
Phone: +86 10 68023502
FAX: +86 10 68023523
EMAIL: linglin.he@lauterbach.com

China Shenzhen

Lauterbach Technologies Co., Ltd
1406/E Xihaimingzhu Building
No.1 Taoyuan Road, Nanshan District
Shenzhen 518052, P.R. China
Phone: +86 755 8621 0671
FAX: +86 755 8621 0675
EMAIL: emily.zhang@lauterbach.com

China Suzhou

Lauterbach Technologies Co., Ltd
Mr. Linglin He
Hengyu Square, Rm 709
No. 188, Xing Hai Street
Suzhou, 215021 P.R. of China
Phone: +86 512 6265 8030
FAX: +86 512 6265 8032
EMAIL: info_cn@lauterbach.com

Czech Republic

Lauterbach GmbH
Alltaufstr. 40
D-85635 Höhenkirchen-Siegertsbrunn
Phone: +49 8102 9876 130
FAX: +49 8102 9876 187
EMAIL: sales@lauterbach.com

Denmark

Nohau Danmark A/S
Mr. Flemming Jensen
Hørkær 26, Plan 4
DK-2730 Herlev
Phone: +45 44 52 16 50
FAX: +45 44 52 26 55
EMAIL: info@nohau.dk

Egypt

Lauterbach GmbH
Alltaufstr. 40
D-85635 Höhenkirchen-Siegertsbrunn
Phone: +49 8102 9876 130
FAX: +49 8102 9876 187
EMAIL: sales@lauterbach.com

Finland

Nohau Solutions Finland
Mr. Martti Viljainen
Tekniikantie 14
FI-02150 Espoo
Phone: +358 40 546 0142
FAX: +358 9 2517 8101
EMAIL: sales@nohau.fi

France

Lauterbach S.A.R.L.
Mr. Jean-Pierre Paradiso
Europarc - Le Hameau B
135 Chemin Des Bassins
F-94035 Créteil Cedex
Phone: +33 1 49 56 20 30
FAX: +33 1 49 56 20 39
EMAIL: info_fr@lauterbach.com

Germany

Lauterbach GmbH
Sales Team Germany
Alltaufstr. 40
D-85635 Höhenkirchen-Siegertsbrunn
Phone: +49 8102 9876 190
FAX: +49 8102 9876 187
EMAIL: sales@lauterbach.com

Greece

Lauterbach GmbH
Alltaufstr. 40
D-85635 Höhenkirchen-Siegertsbrunn
Phone: +49 8102 9876 190
FAX: +49 8102 9876 187
EMAIL: sales@lauterbach.com

Hungary

Lauterbach GmbH
Alltaufstr. 40
D-85635 Höhenkirchen-Siegertsbrunn
Phone: +49 8102 9876 190
FAX: +49 8102 9876 187
EMAIL: sales@lauterbach.com

India-Bangalore

Electro Systems Associates Pvt. Ltd.
Mr. G. V. Gurunatham
S-606, World Trade Center
Malleswaram West, No.26/1, Dr. Rajkumar
Road
India - Bangalore 560055
Phone: +91 80 67648888
FAX: +91 80 23475615
EMAIL: Trace32sales@esaindia.com

India-Chennai

Electro Systems Associates Pvt. Ltd.
Mr. D. Kannan
No.109 /59A - Ground Floor
IV Avenue, Ashok Nagar
India - Chennai - 600 083 Tamilnadu
Phone: +91 044-24715750
FAX: +91 44 24715750
EMAIL: chennai@esaindia.com

India-Delhi

Electro Systems Associates Pvt. Ltd.
Mr. R.K. Bhandari
No. 705, 7th Floor, Laxmi Deep
Shivajinagar
India - Delhi - 110 092
Phone: +91 11-22549351
FAX:
EMAIL: delhi@esaindia.com

India-Hyderabad

Electro Systems Associates Pvt. Ltd.
Mr. C.V.M. Sri Ram Murthy
Shop No. 14, "Global Enclave"
Bhagyanagar Colony, Kukat pally
India - Hyderabad 500 072
Phone: +91 40-23063346
FAX: +91 40-23063346
EMAIL: hyderabad@esaindia.com

India-Kolkata

Electro Systems Associates Pvt. Ltd.
Mr. Arun Roy
India - Kolkata
Phone: +91 98305 78843
FAX:
EMAIL: kolkata@esaindia.com

India-Pune

Electro Systems Associates Pvt. Ltd.
Mr. R K Bhandari
Shriram Complex, 1126/1, Model Colony
Shivajinagar
India - Pune - 411 016
Phone: +91 20 - 30462035 / 25663
FAX: +91 20-25677202
EMAIL: pune@esaindia.com

Ireland

Lauterbach Ltd.
Mr. Richard Copeman
11 Basepoint Enterprise Centre
Stroudley Road
Basingstoke, Hants RG24 8UP
Phone: 0044-118 328 3334
FAX:
EMAIL: info_uk@lauterbach.com

Israel

Itec Ltd.
Mr. Mauri Gottlieb
P.O.Box 10002
IL-Tel Aviv 61100
Phone: +972 3 6491202
FAX: +972 3 6497661
EMAIL: general@itec.co.il

Italy

Lauterbach Srl
Mr. Maurizio Menegotto
Via Enzo Ferrieri 12
I-20153 Milano
Phone: +39 02 45490282
FAX: +39 02 45490428
EMAIL: info_it@lauterbach.com

Japan

Lauterbach Japan, Ltd.
Mr. Kenji Furukawa
3-8-8 Shinyokohama
Kohoku-ku, Nisso 16th Building
Yokohama-shi, Japan 222-0033
Phone: +81 45 477 4511
FAX: +81 45 477 4519
EMAIL: info@lauterbach.co.jp

Luxembourg

Tritec Benelux B.V.
Mr. Robbert de Voogt
Stationspark 550
NL-3364 DA Sliedrecht
Phone: +31 184 41 41 31
FAX: +31 184 42 36 11
EMAIL: software@tritec.nl

Malaysia

Flash Technology
Mr. Teo Kian Hock
No 61, # 04-15 Kaki Bukit Av 1
Shun Li Industrial Park
SGP-Singapore 417943
Phone: +65 6749 6168
FAX: +65 6749 6138
EMAIL: teokh@flashtech.com.sg

Mexico

Lauterbach Inc.
Mr. Udo Zoettler
4 Mount Royal Ave.
USA-Marlborough, MA 01752
Phone: +1 508 303 6812
FAX: +1 508 303 6813
EMAIL: info_us@lauterbach.com

Netherlands

Tritec Benelux B.V.
Mr. Robbert de Voogt
Stationspark 550
NL-3364 DA Sliedrecht
Phone: +31 184 41 41 31
FAX: +31 184 42 36 11
EMAIL: software@tritec.nl

New Zealand

Embedded Logic Solutions P/L
Mr. Ramzi Kattan
Suite 2, Level 3
144 Marsden Street
Parramatta NSW 2150
Phone: +61 2 9687 1880
FAX: +61 2 9687 1881
EMAIL: sales@emilogic.com.au

Norway

Nohau Solutions AB
Mr. Jörgen Nilsson
Derbyvägen 6D
SE-21235 Malmö
Phone: +46 40 592 206
FAX: +46-40 592 229
EMAIL: Jorgen.nilsson@nohau.se

Poland

QUANTUM Sp. z o.o.
Mr. Aleksander Bil
ul. Jeleniogorska 6
54-056 Wrocław
Phone: +48 71 362 6356
FAX: +48 71 362 6357
EMAIL: info@quantum.com.pl

Portugal

Captura Electronica, SCCL
Mr. Juan Martinez
c/Duero, 40
E-08031 Barcelona
Phone: +34 93 429 5730
FAX: +34 93 407 0778
EMAIL: info@captura-el.com

Romania

Lauterbach GmbH
Altlaufstr. 40
D-85635 Höhenkirchen-Siegersbrunn
Phone: +49 8102 9876 130
FAX: +49 8102 9876 187
EMAIL: sales@lauterbach.com

Russia

RTSoft
Mr. Alexey Isaev
Nikitinskaya 3
RUS-105037 Moscow
Phone: +7 495 742 6828
FAX: +7 495 742 6829
EMAIL: sales@rtsoft.msk.ru

Singapore

Flash Technology
Mr. Teo Kian Hock
No 61, # 04-15 Kaki Bukit Av 1
Shun Li Industrial Park
SGP-Singapore 417943
Phone: +65 6749 6168
FAX: +65 6749 6138
EMAIL: teokh@flashtech.com.sg

South Korea, Pangyo

Hancom MDS Inc.
Mr. Dongwook Jun
3FL, Hancom Tower
49, Daewangpangyo-ro 644, Bundang-gu
Seongnam-si, Gyeonggi-do, 463-400, ROK
Phone: +82-31-627-3000
FAX: +82-31-627-3100
EMAIL: trace32@hancommds.com

Spain

Captura Electronica, SCCL
Mr. Juan Martinez
c/Duero, 40
E-08031 Barcelona
Phone: +34 93 429 5730
FAX: +34 93 407 0778
EMAIL: info@captura-el.com

Sweden

Nohau Solutions AB
Mr. Jörgen Nilsson
Derbyvägen 6D
SE-21235 Malmö
Phone: +46 40 592 206
FAX: +46 40 592 229
EMAIL: Jorgen.nilsson@nohau.se

Switzerland

JDT Jberg DatenTechnik
Mr. Andreas Jberg
Zimmereistrasse 2
CH-5734 Reinach AG
Phone: +41 62 7710 886
FAX:
EMAIL: Andreas.Jberg@jdt.ch

Taiwan

Superlink Technology Corp.
Mr. Sulin Huang
3F-8, No. 77, Sec. 1, Xintaiwu Rd., Xizhi District,
New Taipei City 22101, Taiwan, R.O.C.
Phone: +886 2 26983456
FAX: +886 2 26983535
EMAIL: info.stc@superlink.com.tw

Tunisia

Lauterbach Consulting S.A.R.L.
Mr. Khaled Jmal
Route El Ain Km 3.5
TN-3062 Sfax
Phone: +216-31361061
FAX: +216-74611723
EMAIL: info_tn@lauterbach.com

Turkey-1

Tektronik Muh. ve Tic. A.S.
Mr. Hakan Yavuz
CyberPlaza B-Blok, 702B
Bilkent
06800 Ankara
Phone: +90 312 437 3000
FAX: +90 312 437 1616
EMAIL: info@tektronik.com.tr

Turkey-2

G3TEK Embedded Technologies Ltd.
Mr. Celal Aygun
Ilkyerlesim Mah. 445.
Sok. No: 48
06370 Battikent/Ankara
Phone: +90 312 3324769
FAX: +90 312 3324769
EMAIL: info@g3tek.com

UK

Lauterbach GmbH
Mr. Richard Copeman
Altlaufstr. 40
D-85635 Höhenkirchen-Siegertsbrunn
Phone: +49 8102 9876 190
FAX: +49 8102 9876 187
EMAIL: sales@lauterbach.com

USA East

Lauterbach Inc.
Mr. Udo Zoettler
4 Mount Royal Ave.
USA-Marlborough, MA 01752
Phone: +1 508 303 6812
FAX: +1 508 303 6813
EMAIL: info_us@lauterbach.com

USA West

Lauterbach Inc.
Mr. Bob Kupyn
1111 Main Street, Suite 620
USA-Vancouver, WA, 98660
Phone: +1 503 524 2222
FAX: +1 503 524 2223
EMAIL: bob.kupyn@lauterbach.com

Additional Information

<http://www.lauterbach.com>

Lauterbach GmbH

Altlaufstr. 40
D-85635 Höhenkirchen-Siegertsbrunn
Tel. ++49 8102 9876-0 FAX -999
info@lauterbach.com
http://www.lauterbach.de

Lauterbach Inc.

4 Mount Royal Ave.
Marlboro MA 01752
Phone (508) 303 6812 FAX (508) 303 6813
info_us@lauterbach.com
http://www.us.lauterbach.com

Lauterbach Ltd.

11 Basepoint Enterprise Ctre Stroudley Road
Basingstoke, Hants RG24 8UP
Phone ++44-1256-333-690 FAX -661
info_uk@lauterbach.com
http://www.lauterbach.co.uk

Lauterbach S.A.R.L.

135 Chemin Des Bassins
F-94035 Créteil Cedex
Phone ++33-149-562-030
FAX ++33-149-562-039
info_fr@lauterbach.com
http://www.lauterbach.fr

Lauterbach Japan, Ltd.

3-9-5 Shinyokohama Kouhoku-ku
Yokohama-shi Japan 222-0033
Phone ++81-45-477-4511 FAX -4519
info_j@lauterbach.com
http://www.lauterbach.co.jp

Lauterbach s.r.l.

Lauterbach s.r.l.
Via Enzo Ferrieri 12
I-20153 Milano
Phone ++39 02 45490282
FAX ++39 02 45490428
info_it@lauterbach.it
http://www.lauterbach.it

Suzhou Lauterbach Consulting Co.,Ltd.

Room 1605, Xing Hai International Square
No.200, Xing Hai Street
Suzhou, 215021 PR of China
Phone: 0086-512 6265 8030
FAX: 0086-512 6265 8032
info_cn@lauterbach.cn
http://www.lauterbach.cn

Disclaimer

The information presented is intended to give overview information only. Changes and technical enhancements or modifications can be made without notice.